# **ENGDUINO LIBRARIES: THE INFRARED**

The infrared transceiver allows two (or more) Engduinos to talk to each other over a distance of upto about 50-100cm. This is the most complex of the libraries in terms of basic functionality, but it is easy enough to use once you are a competent programmer.

## **HEADER**

#include <EngduinoIR.h>

## SETUP()

EngduinoIR.begin();

## **BASIC FUNCTIONS**

To make use of the IR, you must understand the concept of arrays. Take some time to revise this if you need to before trying the exercises in here. Because the IR is about communication, you will need two Engduinos to do anything useful.

In terms of basic functions, you can send a single character (byte) at a time. So, for example, to send the character 'c' we do the following.

```
EngduinoIR.send('c');
```

And, to receive, you should execute the following code on the destination:

Write code for a sender, which sends a character every second. On a different Engduino, write the code for a receiver, which repeatedly executes a receive and prints the result.

## MORE ADVANCED FUNCTIONS

Rather than sending a single byte at a time, you can send upto 12 bytes:

If you don't want to wait forever for an incoming message to arrive, you can set a timeout. When the function call returns, either (a) a message has been received or (b) the call has timed out. In the first case, the length of the message is returned, in the second, a negative number is returned:

If you set the timeout to zero, the **recv** function will block forever - as it did when we omitted the timeout value.

#### IDEAS FOR PROJECTS WITH THE IR

- Make an Engduino send the word "Hello" when a button is pressed, and print out any
  message it receives. Try this between two Engduinos and vary the distance between them.
   You will probably notice that at some point, the message isn't received correctly.
- To deal with this, we need to know when a message has been received correctly. There are several ways of doing this: for example, you could use a parity bit or a cyclic redundancy check (CRC) algorithm. Search online for these terms and see whether you can implement them for the Engduino
- Write a simple communications protocol. Each Engduino should periodically send a message that tells other Engduinos that it is there. It should also listen for other Engduinos sending this message. When two Engduinos meet, one of them should flash the LEDs red, the other should flash them blue. It doesn't matter which does what, so long as one is red and the other blue. You shouldn't use the button at all this should happen automatically when they are in range of each other.
- Note for Engduino v2+: because of the way in which the IR is wired in v2+, which was changed from v1 to allow additional interfacing capabilities, the IR communications will not be able to decode the signal sent by a TV remote. It may still be able to distinguish between some buttons, but that is beyond the scope of this document.